

What is claimed is:

1 1. A method of configuring an RF network, the network comprising at least
2 two nodes, each having a controller, a data store, and at least one transceiver for communicating
3 with other nodes, each transceiver having a unique identifier, the method comprising the steps of:
4 (a) assigning a predetermined value to a variable n ;
5 (b) selecting one certain of the nodes and associating it with the value of n ;
6 (c) paging all other nodes from a node associated with the value of n ;
7 (d) in a node associated with the value of n , noting nodes which reply to paging and
8 associating them with the value of $(n+1)$;
9 (e) making all nodes associated with the value of n or with lower values unresponsive to
10 paging;
11 (f) incrementing the value of n ; and
12 (g) repeating steps (c) through (f) until no nodes reply to paging,
13 whereby nodes beyond transmission range of other nodes but within transmission range of
14 intermediate nodes become known to said other nodes and become accessible to said other nodes
15 by relaying through said intermediate nodes.

1 2. The method of claim 1, wherein said certain node is further a gateway to
2 another network.

1 3. The method of claim 1, further comprising step:
2 (h) repeating steps (a) through (g) with a different node selected as the certain node.

1 4. The method of claim 3, wherein any node selected as the certain node is
2 further a gateway to another network.

1 5. The method of claim 1, wherein the RF network is a short-range RF
2 network.

1 6. The Method of claim 5, wherein the short-range RF network is a
2 Bluetooth network.

1 7. The method of claim 1, wherein:
2 if a node comprises at least two transceivers, the first one to answer paging is designated
3 as a slave transceiver of the RF network and least one of the other transceivers is designated as a
4 master transceiver of the RF network, and each transceiver designated as a master does not
5 answer paging.

1 8. The method of claim 7 wherein in step (c) paging is performed by the
2 master.

1 9. The method of claim 1, wherein a node further includes a transceiver for
2 communication with wireless terminals, whereby a wireless terminal in transmission range of a
3 node may communicate with another wireless terminal in transmission range of a node.

1 10. The method of claim 1, wherein a transceiver further communicates with
2 wireless terminals, whereby a wireless terminal in transmission range of a node may
3 communicate with another wireless terminal in transmission range of a node.

1 11. The method of claim 2, wherein a node further includes a transceiver for
2 communication with wireless terminals, whereby a wireless terminal in transmission range of a
3 node may communicate with another wireless terminal in transmission range of a node or with
4 an entity on said other network.

1 12. The method of claim 1, wherein each transceiver further has a password
2 associated with it, and wherein:
3 in step (c), passwords are included in paging; and
4 a node does not reply to paging unless the password included in paging matches the
5 password associated with the transceiver.

1 13. A method of configuring an RF network, the network comprising a
2 plurality of network nodes for communicating with other nodes, each having a controller unit
3 and a data store, the method comprising the steps of:

- 4 a) storing identifiers of all nodes on the network in a data store accessible to at least one
5 node;
6 b) paging from the at least one node other nodes;
7 c) detecting other nodes within the coverage area of the at least one node by receiving
8 responses of said detected nodes to paging;
9 d) updating information regarding said detected nodes according to the received
10 responses of said detected nodes to paging;
11 e) associating said detected nodes with a first value of a dynamic variable, the value of
12 the dynamic variable depending on the placement of each said detected node in
13 the network; and
14 f) propagating the updated information to said detected nodes in the network.

1 14. The method of claim 13, wherein each node comprises a transceiver
2 connected to the controller unit for communicating with other transceivers, each
3 transceiver having a unique identifier.
4

1 15. The method of claim 14, further comprising:

- 2 g) incrementing the value of the dynamic variable;
- 3 h) paging from a transceiver of each said detected node other transceivers;
- 4 i) detecting other nodes within the coverage area of the transceiver of each said detected
- 5 node by receiving responses of said newly detected nodes' transceivers to paging;
- 6 j) updating information regarding said newly detected nodes' transceivers to paging;
- 7 k) associating newly detected nodes of the network with the incremented value of the
- 8 dynamic variable; and
- 9 l) propagating the updated information to all detected nodes in the network.

1 16. The method of claim 15, further comprising repeating steps g) through l)

2 until every node of the network is configured.

1 17. The method of claim 13, wherein the at least one node selected as a

2 control node and said control node is further a gateway to another network.

1 18. The method of claim 15, further comprising the step of repeating steps (a)

2 through (l) with a different node selected as a control node.

1 19. The method of claim 18, wherein any node selected as the control node is

2 further a gateway to another network.

1 20. The method of claim 13, wherein the RF network is a Bluetooth network.

1 21. The method of claim 15, wherein:

2 if a node comprises at least two transceivers, the first one to answer paging is designated
3 as a slave transceiver of the RF network and least one of the other transceivers is designated as a
4 master transceiver of the RF network, and each transceiver designated as a master does not
5 answer paging.

 22. The method of claim 21, wherein paging is performed by the master.

1 23. The method of claim 15, wherein a node further includes a transceiver for
2 communication with wireless terminals, whereby a wireless terminal in transmission range of a
3 node may communicate with another wireless terminal in transmission range of a node.

1 24. The method of claim 15, wherein a transceiver further functions to
2 communicate with wireless terminals, whereby a wireless terminal in transmission range of a
3 node may communicate with another wireless terminal in transmission range of a node.

1 25. The method of claim 16 wherein a node further includes a transceiver for
2 communication with wireless terminals, whereby a wireless terminal in transmission range of a
3 node may communicate with another wireless terminal in transmission range of a node or with
4 an entity on said other network.

1 26. The method of claim 15, wherein each transceiver further has a password
2 associated with it, and wherein:
3 passwords are included in paging; and
4 a transceiver does not reply to paging unless the password included in paging matches the
5 password associated with the transceiver.

1 27. The method of claim 16, wherein further:
2 each transceiver has associated with it a portable machine-readable tag containing the
3 transceiver's unique identifier;
4 associated with the network is a tag reader for reading the machine-readable tags; and
5 step (a) comprises substeps:
6 (a1) presenting each tag to the tag reader; and
7 (a2) transferring each output of the tag reader to the data store of the control node.

1 28. The method of claim 26, wherein further:
2 each transceiver has associated with it a portable machine-readable tag containing the
3 transceiver's unique identifier and password;
4 associated with the network is a tag reader for reading the machine-readable tags; and
5 step (a) comprises substeps:
6 (a1) presenting each tag to the tag reader; and
7 (a2) transferring each output of the tag reader to the data store of the first node.

1 29. A self-configuring RF network, the network comprising:
2 a plurality of nodes for communicating wirelessly with other nodes of the RF
3 network, wherein at least one of the nodes is selected as a control node, each node
4 including:
5 a control logic;
6 a data store connected to the control logic;
7 at least one transceiver connected to the control logic and identified by a unique
8 address for communicating wirelessly with other nodes of the network;
9 a transceiver list database connected to the data store for storing updateable
10 information of all transceivers of the RF network for network configuration; and
11 a dynamic variable linked to the transceiver list database for indicating position of
12 each node in the RF network relative to the control node.

1 30. The RF network of claim 29, wherein:
2 if a node comprises at least two transceivers the control logic is arranged to designate the
3 first one to answer paging as a slave transceiver of the RF network and to designate at least one
4 of the other transceivers as a master transceiver of the RF network, and wherein each transceiver
5 designated as a master does not answer paging.

1 31. The RF network of claim 29, wherein a node further includes a transceiver
2 for communicating with wireless terminals, whereby a wireless terminal in transmission range of
3 a node may communicate with another wireless terminal in transmission range of a node.

1 32. The RF network of claim 29, wherein a transceiver further communicates
2 with wireless terminal, whereby a wireless terminal in transmission range of a node may
3 communicate with another wireless terminal in transmission range of a node.

1 33. The RF network of claim 29, wherein the control node is further a gateway to
2 another network.

1 34. The RF network of claim 31, wherein the control node is further a gateway
2 to another network, whereby a wireless terminal in transmission range of a node may
3 communicate with a terminal on said other network.

1 35. The RF network of claim 29, wherein:
2 associated with each transceiver is a unique password;
3 provided with each transceiver is a machine-readable tag on which is recorded the
4 transceiver's unique address and password, and
5 associated with the control node is a reader for reading the unique addresses and
6 passwords from the tags and storing them in the first node's transceiver list.

1 36. The RF network of claim 35, wherein:

2 (a) a transceiver of the control node pages other transceivers in its transceiver list;

3 (b) a transceiver of the control node detects other nodes within its coverage area according
4 to response of said other transceivers to paging;

5 (c) the control node's transceiver list is updated according to said response of said other
6 transceivers to paging;

7 (d) the control logic associates detected transceivers' information in the control node's
8 transceiver list with a current value of the dynamic variable; and

9 (e) the control logic directs propagating the updated contents of the control node's
10 transceiver list to all detected nodes in the network.

1 37. The RF network of claim 36, wherein:

2 (f) the control logic of each detected node directs incrementing the dynamic variable;

3 (g) a transceiver of each node pages other transceivers in its transceiver list;

4 (h) each node detects other nodes within the coverage area of its transceiver according to
5 response of said other transceivers to paging;

6 (i) each node's control logic directs updating the node's transceiver list according to
7 response of said other transceivers to paging;

8 (j) the node's control logic associates detected transceivers' information in the node's
9 transceiver list with a current value of the dynamic variable; and

10 (k) the control logic directs propagating the updated contents of each node's transceiver
11 list to all detected nodes in the network.

1 38. The RF network of claim 37, wherein functions (g) through (k) are

2 repeated until all nodes of the network are detected.

1 39. The RF network of claim 38, wherein:

2 the control logic of each node computes an indication of current load carried by the node;

3 each node dynamically transmits its load indication at least to nodes within its transmission
4 range; and

5 each node dynamically receives and stores load indications received from other nodes.

1 40. The RF network of claim 39, wherein the control logic of each node
2 dynamically calculates routes for transmitting messages to the first node including relays through
3 other nodes for nodes not within transmission distance of the control node.

1 41. The RF network of claim 40 wherein a node not within transmission
2 distance of the control node selects routes to the first node traversing the fewest other nodes.

1 42. The RF network of claim 41 wherein if several routes traverse the fewest
2 other nodes, a route is selected which has traverses nodes having least aggregate load indication.

1 43. The RF network of claim 29, wherein the RF network is a short-range RF
2 network.

1 44. The RF network of claim 43, wherein the short-range RF network is a
2 Bluetooth network.

1 45. The RF network of claim 29, wherein a transceiver not within transmission
2 range of a certain node communicates with the certain node by relaying through other of the
3 nodes.

1 46. A node for use in a self-configuring RF network, comprising:

2 a backbone transceiver identified by a unique address and associated with a password, for
3 communicating with other nodes of the network; and

4 control logic configured to detect when the backbone transceiver receives a paging
5 message directed to its unique address, and in response, to direct that:

6 a password received in the paging message be verified as the password associated
7 with the backbone transceiver;

8 a node transceiver list received in the paging message, containing addresses and
9 passwords of other nodes in the network, be received and stored;

10 a value "n" of a dynamic variable received in the paging message be received and
11 stored; and

12 the node becomes unresponsive to further paging messages.

1 47. The node according to claim 46, further comprising a second backbone
2 transceiver, and wherein the control logic is further configured to direct that:

3 the backbone transceiver which received the paging message is designated a slave
4 transceiver;

5 the other backbone transceiver is designated a master transceiver;

6 the value "n" of the dynamic variable is incremented;

7 the master transceiver transmits to each transceiver in the node transceiver list a paging
8 message including:

9 the paged transceiver's password;

10 the node transceiver list; and

11 the value of the dynamic variable.

1 48. A node according to claim 46, comprising a transceiver for communicating
2 with mobile terminals, whereby a mobile terminal in transmission range of a node may
3 communicate with another mobile terminal in transmission range of a node.

1 49. A node according to claim 46, wherein a backbone transceiver also
2 communicates with mobile terminals, whereby a mobile terminal in transmission range of a node
3 may communicate with another mobile terminal in transmission range of a node.

1 50. A node according to claim 46 wherein the backbone transceivers are short-
2 range RF transceivers.

1 51. A node according to claim 50 wherein the transceivers are Bluetooth
2 transceivers.

1 52. A self-configuring RF network, the network comprising:
2 a plurality of nodes for communicating wirelessly with other nodes of the RF network,
3 wherein at least one of the nodes is selected as a control node, each node including:
4 a control logic;
5 a data store connected to the control logic;
6 at least one transceiver connected to the control logic identified by a unique address for
7 communicating wirelessly with other nodes of the network either directly or through one or more
8 relay nodes; and
9 software means operative on the control logic for:
10 maintaining in the data store a transceiver list database containing
11 updateable information of all transceivers of the RF network for network
12 configuration;
13 indicating, with a dynamic variable linked to the transceiver list database,
14 position of each node in the RF network in relation to the control node;
15 periodically communicating wirelessly among the nodes of the RF network
16 for exchanging updated configuration information and dynamic variable
17 information; and

18 updating current network configuration information and dynamic variable
19 information within the data store.

1 53. The RF network of claim 52, wherein the software means is further
2 operative for determining, according to dynamic variable information, a route traversing the
3 fewest nodes from a node to the control node.

1 54. The RF network of claim 53, wherein the software means is further
2 operative for:
3 dynamically updating load information of a node and at least nodes within communication
4 distance of the node; and
5 selecting, according to load information, a route traversing least loaded nodes from among
6 two or more routes traversing equal numbers of nodes from a node to the control node.

1 55. A method of configuring an RF network, the method comprising the steps
2 of:
3 electronically maintaining, for network configuration, a transceiver list database
4 containing updateable information regarding all transceivers of the RF network;
5 indicating position of each node in RF network in relation to a control node with a
6 dynamic variable linked to the transceiver list database;
7 periodically communicating wirelessly between nodes of the RF network for exchanging
8 updated configuration information and dynamic variable information; and

- 9 updating current network configuration information and dynamic variable information
- 10 within the transceiver list database.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000